



PagesOS 3 Software Update



Latest version overview can be found [here](#).

Compatibility

OS3 firmware is compatible with all current SmallHD monitors (FOCUS series monitors, 500 series monitors, 700 series monitors, Cine 7 series monitors, all Bolt monitors, 1300 series monitors, 1700 series monitors, 2400 series monitors, and 3200 series monitors).



OS3 is **not compatible** with legacy monitors (DP1, DP6, DP4, AC7, and DP7-PRO).

How to Install OS3 Firmware



CAUTION: Make sure you do not lose power during firmware update

Download the [latest firmware update](#)

1. Click the .zip download file to extract the .bin (firmware file).
2. Drag and drop the .bin file onto your SD card
 - Card must be 16 GB or smaller
 - Formatted as **FAT** or **FAT32** for Windows, **MS-DOS (FAT)** for macOS (if partitioned, select the MBR Master Boot Record option under Scheme)
3. Remove SD Card from computer or card reader attached to computer
4. Insert SD card into your SmallHD monitor
5. Turn on your monitor
6. Swipe/toggle left to the monitor's Settings Menu
7. Select "FIRMWARE" in Settings Menu and follow on-screen prompts
8. Once the firmware is installed and the on-screen prompts tell you to reboot your monitor – Hold down the power button for at least 5 seconds and then release.
9. Press the power button again to begin operating your SmallHD monitor with the new firmware installed.



How to Format an SD Card

You must format the SD card using a computer. The monitor cannot format the card.

Windows Instructions

Formatting a card in Windows

macOS Instructions

Format your card using Disk Utility.

Click **Erase** to begin the formatting process.

When choosing the format, be sure to select **MS-DOS (FAT)**.