



Multi-View Page Setup

All 4K Production Monitors can display up to four different video feeds (Views) via the Multi-View Page. This includes any combination of available inputs (**4x** 12G SDI, **1x** HDMI). Additionally, the same Input can be used up to four times.

Add New Multi-View Page

1. Press the Settings Button (**H**) on the front panel of the monitor.
2. Using the Menu Joystick, navigate and select **Multi** under **UTILITIES**.

Assigning Inputs to Multi-View

1. Using the Menu Joystick, navigate to and select the Multi-View Page (**MULTI**).



2. Select the desired **VIEW** (1 to 4), select an **INPUT**, then choose one of the five input options.



Adding Tools to Multi-View

Monitor Tools can be enabled on every view on the Multi-View Page.

1. From the Multi-View page, press the Menu Joystick to display the **VIEWS** and **ARRANGE** menus, then press it again to select the desired View (1 to 4).
2. Press the Menu Joystick to select **TOOLS**, then press down to select **+ ADD TOOL**.



3. Select a tool from the list of available Tools.



Changing the Multi-View Layout

The Multi-View Page Views can be arranged using four different configurations.



1. Using the Menu Joystick, navigate to and select the Multi-View Page (**MULTI**), then scroll down to **ARRANGE**.
2. Select the desired arrangement (a preview of each arrangement will populate in real time).



Custom Color Pipe Settings

Different cameras/sources on the Multi-View Page may require different [Color Pipe](#) settings. Having different Color Pipe settings on the various views of the Multi-View Page allows filmmakers to compare things like LOG vs LUT and SDR vs HDR.

1. To adjust the Color Pipe setting per source, Joystick Press on the Multi-View Page, then select the desired View.
2. Select COLOR PIPE, then choose a Color Pipe setting. **NOTE: Color Pipe presets can be adjusted via Monitor Settings > feed > Color Pipe**